

# Probabilistic Graphical Models in Computer Vision

Lecture: Dr. Tao Wu  
Exercises: Yuesong Shen, Zhenzhang Ye  
Summer Semester 2019

Computer Vision Group  
Institut für Informatik  
Technische Universität München

## Weekly Exercises 7

Room: 02.09.023

Wednesday, 03.07.2019, 12:15 - 14:00


### MCMC sampling (Due: 01.07) (14+4 Points)

**Exercise 1** (4 Points). (regular  $\Rightarrow$  irreducible and aperiodic) Show that if a Markov chain is regular, then it is irreducible and aperiodic.

**Exercise 2** (8 Points). (Properties of transition matrix) For Markov chains with finite state spaces, the transition kernel can be represented in matrix form:  $T_{l,m} = Pr(X_i = m | X_{i-1} = l)$  for any time step  $i$ . For each of the transition matrices in the following, determine whether it is irreducible / aperiodic:

$$\begin{array}{cccc} \text{(a)} & \text{(b)} & \text{(c)} & \text{(d)} \\ \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} & \begin{bmatrix} 1 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & 1 & 0 \end{bmatrix} & \begin{bmatrix} 0 & 1 & 0 \\ 0 & 0 & 1 \\ 1 & 0 & 0 \end{bmatrix} & \begin{bmatrix} 0.6 & 0.4 \\ 0.4 & 0.6 \end{bmatrix} \end{array}$$

**Exercise 3** (6 Points). (State transition diagram and stationary distribution) A transition matrix of a finite state Markov chain can be visualized as a diagram with nodes representing the states and directed arcs the possible transitions and its probability. For example, a diagram for the transition matrix  $\begin{bmatrix} 0.7 & 0.3 \\ 1.0 & 0.0 \end{bmatrix}$  looks like the following:



For each of the transition matrices (a), (c), (d) in Exercise 2, draw a corresponding diagram, write down the set of stationary distributions, and for each stationary distribution indicate the set of initial distributions that will converge towards it.

## Programming (Due:08.07)

(12 Points)

In this programming exercise, you are asked to use mean field and Gibbs sampling for image segmentation. See the ipython file for more details.